



GE
Lighting

33890 - GE garage & basement circline 32 watt T9 circline 1-pack

FC12T9/CW

- ☞ Ideal for office and utility use
- ☞ Lasts up to 8 years!
- ☞ 1.1 inch diameter T9 circline with 4-pin (g10q) base
- ☞ 4100K cool white light appearance
- ☞ Cool white light perfect for sizable spaces
- ☞ For use in large spaces such as basements and garages
- ☞ GE garage & basement circline fluorescent bulbs' cool white light is perfect for illuminating sizable spaces throughout your home. Use in large open spaces in your home including finished and unfinished basements, garages and rec rooms
- ☞ Lasts 5.5 years based on 6 hours per day usage

Product Photo



GENERAL CHARACTERISTICS

Base Description	4-Pin
Base Type	Pin/Plug-In
Mercury Content	7 mg
Mercury-Picogram per mean lm hr	399.5
Starting Temp (MIN) C-degrees	10 °C
Bulb Material	Lead glass
Rated Life Hours-nominal	12000 h
Primary Application	Full Wattage Garage & Basement
Product Technology	Linear Fluorescent
Base	G10q
Bulb Shape	T9

PHOTOMETRIC CHARACTERISTICS

Mean Lumens nominal	1460 lm
Nominal Initial Lumen per Watt	61
Initial Lumens-nominal	1950 lm
Color Rendering Index-CRI	60
Color Temperature	4100 K

PRODUCT INFORMATION

Product Code	33890
Description	FC12T9/CW
Alternative Unit Of Measure	Case
Standard Package Quantity	12
Ean UPC	043168980401
Standard Package GTIN	00043168338905
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	12
Sales Unit	Unit
UCC	043168338905

DIMENSIONS

Bulb Diameter (DIA) <Max>	1.22 in
Bulb Diameter (DIA) <Min>	1.03 in
Diameter	1.125 in
Nominal Length	12 in

ELECTRICAL CHARACTERISTICS

Current Crest Factor (MAX)	1.7
Open Circuit Voltage (rapid start) Min @ Temperature	230.00 V @ 10 °C
Cathode Resistance Ratio - Rh/Rc (MIN)	4.250
Cathode Resistance Ratio - Rh/Rc (MAX)	6.500
Rated power (Watts)	32 W



CAUTIONS & WARNINGS

Caution

- Lamp may shatter and cause injury if broken
- Wear safety glasses and gloves when handling lamp.
- Do not use excessive force when installing lamp.

Warning

- Risk of Electric Shock
- Turn power off before inspection installation or removal.





Nov 2, 2015 6:40:04 PM For additional information, visit www.gelighting.com