



Commercial Products & Solutions




Where to Buy | FAQs | Contact Us | EliteNet

Products > 97613

97613 - F26DBX/841/ECO4P

GE Ecolux® Biax® T4 - Facilities; Retail Display; Hospitality; Office; Restaurant; Warehouse





	0 Fl
Lamp type	Compact Fluorescent - Plug-In
Bulb	T4
Base	G24q-3
Wattage	26
Voltage	120/105
Rated Life	12000 hrs
Starting Temperature (MIN)	0 ℃ (32 ℉)
Cathode Resistance	2.700 Ohm
LEED-EB MR Credit	232 picograms Hg per mean lumen hour
Rated Life (rapid start) @ Time	20000 h @ 12 h
Additional Info	Dimmable with appropriate dimming ballast., End of Life Protection (EOL), TCLP compliant
Primary Application	Facilities; Retail Display; Hospitality; Office; Restaurant; Warehouse



PHOTOMETRIC CHARACTERISTICS Initial Lumens 1710 Mean Lumens 1440 Nominal Initial 65 Lumens per Watt Color Temperature 4100 K Color Rendering 82 Index (CRI)

ELECTRICAL CHARACTERISTICS				
Current (max)	5.2500 A			
Open Circuit Voltage (after preheating) (MAX)	240 V			
Open Circuit Voltage Across Starter (MIN)	198 V			
Lamp Current	0.325 A			
Preheat Voltage (MIN)	4 V			
Current Crest	1.7			

Catalogs Testimonials Disposal Policies & Recycling Information

Factor (MAX)	
Supply Current Frequency	60 Hz
DIMENSIONS	
Maximum Overall Length (MOL)	6.4000 in (162.5 mm)
Nominal Length	6.400 in (162.5 mm)
Base Face to Top of Lamp	5.800 in (147.3 mm)

PRODUCT INFORMATION

Product Code	97613
Description	F26DBX/841/ECO4P
ANSI Code	60901-IEC-2562-2
Standard Package	BUNDLE
Standard Package Quantity	50
Sales Unit	Unit
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	50
UPC	043168976138

COMPATIBLE GE BALLASTS

COMPATIBLE GE BALLASTS						
Product Code	Description	# of Bulbs	Power Factor	Ballast Factor		
71434	GEC218- MVPS-3W	1	99.0	1.0		
<u>71432</u>	GEC218- MVPS-BES	1	99.0	1.0		
71433	GEC218- MVPS-SE	1	99.0	1.0		
<u>71445</u>	GEC226- MVPS-3W	1	99.0	1.0		
71443	GEC226- MVPS-BES	1	99.0	1.0		
71444	GEC226- MVPS-SE	1	99.0	1.0		

A CAUTIONS & WARNINGS

See list of cautions & warnings.

NOTES

- 4-Pin lamp minimum starting temperature is a function of the ballast. Most ballasts are rated with a minimum starting temperature of 50 degrees F (10 C). Ballasts are also available that provide reliable starting to 0 degrees F (-18C) and -20 F (-29C).
- Based on 60Hz reference circuit.
- Fluorescent lamp lumens decline during life

Return To Top

Home | Products | EliteNet | Education/Resources | Lighting Applications | Where to Buy | FAQs | Contact Us | Site Map

Products for Your Home | Press Room | Corporate | Investor Information | Privacy Policy | Accessibility Statement | Terms of Use Copyright General Electric Company 1997-2009