

Features:

- 6500 Watts, 120/240V
- Economic, portable power
- Honda exclusive DAVR (Digital Auto Voltage Regulation)
- Full frame protection
- Voltage selector switch 120/240V operation

Applications:

- Refrigerator or Freeze (Energy Star)
- Microwave oven
- TV / DVD / Stereo
- Hair dryer
- Coffee maker
- Incandescent lights
- Air compressor
- Bench Grinder (8 in)
- Circular Saw (Heavy Duty 7-1/4 in)
- Concrete vibrator
- Drills
- High-pressure washer (1Hp)
- Table Saw (10 In.)

Honda EG6500

Unit Specifications

Frequency	60Hz
Phase	Single Phase
Voltage	120 / 240 Volts
Sound Level at 30 feet	74 dBA
Fuel Tank Capacity	6.3 Gallons
Run Time	up to 11.0 Hours @ 1/2 load

Power Generation

A/C Output	6500 Watt Maximum 5500 Watt Continuous
Amps	54.2/27.1A Maximum 45.8/22.9A Continuous
D/C Output 12Volt	N/A

Receptacles and Circuit Breakers

1 Receptacle of each	20A 125V Duplex 30A 125V Locking Plug
----------------------	--

Dimensions and Weights

Overall Length	26.8 Inches
Overall Width	22.8 Inches
Overall Height	22.7 Inches
Weight	182 Lbs.

Engine Specifications

Engine Make/Model	Honda GX390
Start Method	Recoil
Fuel Type	Gasoline