

GGC/GGC-V

- Glass body
- Fast-acting
- 1/4" x 1-1/4"
- 1-1/2" Axial leads optional

1/10A through 10A,
250VAC, UL Listed
and CSA Certified

12A and 15A, 125VAC,
UL Listed and CSA
Certified

20A through 30A, 32VAC



STANDARD FUSE
AMPERE RATINGS

| Catalog Number | Axial Lead Cat. No | Ampere Rating | Volts | I.R. |
|----------------|--------------------|---------------|-------|------|
| GGC1/10 | GGC-V1/10 | 1/10A | 250V | 2 |
| GGC1/8 | GGC-V1/8 | 1/8A | 250V | 2 |
| GGC15/100 | GGC-V15/100 | 15/100A | 250V | 2 |
| GGC175/1000 | GGC-V175/1000 | 175/1000A | 250V | 2 |
| GGC3/16 | GGC-V3/16 | 3/16A | 250V | 2 |
| GGC2/10 | GGC-V2/10 | 2/10A | 250V | 2 |
| GGC1/4 | GGC-V1/4 | 1/4A | 250V | 2 |
| GGC3/10 | N/A | 3/10A | 250V | 2 |
| GGC3/8 | GGC-V3/8 | 3/8A | 250V | 2 |
| GGC4/10 | GGC-V4/10 | 4/10A | 250V | 2 |
| GGC1/2 | GGC-V1/2 | 1/2A | 250V | 2 |
| GGC6/10 | GGC-V6/10 | 6/10A | 250V | 2 |
| GGC3/4 | GGC-V3/4 | 3/4A | 250V | 2 |
| GGC8/10 | GGC-V8/10 | 8/10A | 250V | 2 |
| GGC1 | GGC-V1 | 1A | 250V | 2 |
| GGC1-1/4 | GGC-V1-1/4 | 1-1/4A | 250V | 2 |
| GGC1-1/2 | GGC-V1-1/2 | 1-1/2A | 250V | 2 |
| GGC1-3/4 | N/A | 1-3/4A | 250V | 2 |
| GGC1-6/10 | GGC-V1-6/10 | 1-6/10A | 250V | 2 |
| GGC2 | GGC-V2 | 2A | 250V | 2 |
| GGC2-1/4 | GGC-V2-1/4 | 2-1/4A | 250V | 2 |
| GGC2-1/2 | GGC-V2-1/2 | 2-1/2A | 250V | 2 |
| GGC3 | GGC-V3 | 3A | 250V | 2 |
| GGC3-2/10 | GGC-V3-2/10 | 3-2/10A | 250V | 3 |
| GGC4 | GGC-V4 | 4A | 250V | 2 |
| GGC5 | GGC-V5 | 5A | 250V | 2 |
| GGC6 | GGC-V6 | 6A | 250V | 2 |
| GGC6-3/10 | GGC-V6-3/10 | 6-3/10A | 250V | 2 |
| GGC7 | GGC-V7 | 7A | 250V | 2 |
| GGC7-1/2 | N/A | 7-1/2A | 250V | 2 |
| GGC8 | GGC-V8 | 8A | 250V | 2 |
| GGC10 | GGC-V10 | 10A | 250V | 2 |
| GGC12 | GGC-V12 | 12A | 125V | 4 |
| GGC15 | GGC-V15 | 15A | 125V | 4 |
| GGC20 | GGC-V20 | 20A | 32V | 5 |
| GGC25 | GGC-V25 | 25A | 32V | 5 |
| GGC30 | GGC-V30 | 30A | 32V | 5 |

2. 250VAC @ 200A I.R./125VAC @ 10kA I.R.
3. 250VAC @ 10kA I.R.
4. 125VAC @ 10kA I.R.
5. 32VAC @ 1000A I.R.

GGM/GGM-V

- Glass body
- Fast-acting
- 5 mm x 20 mm
- 1-1/2" Axial leads optional

1/16A through 3A,
250VAC, UL Listed and
CSA Certified

4A through 8A,
125VAC, UL Listed and CSA Certified

10A and 15A, 250VAC,
UL Recognized



STANDARD FUSE
AMPERE RATINGS

| Catalog Number | Axial Lead Cat. No | Ampere Rating | Volts | I.R. |
|----------------|--------------------|---------------|-------|------|
| GGM1/16 | GGM-V1/16 | 1/16A | 250V | 2 |
| GGM1/10 | GGM-V1/10 | 1/10A | 250V | 3 |
| GGM1/8 | GGM-V1/8 | 1/8A | 250V | 3 |
| GGM2/10 | GGM-V2/10 | 2/10A | 250V | 3 |
| GGM1/4 | GGM-V1/4 | 1/4A | 250V | 3 |
| GGM3/10 | GGM-V3/10 | 3/10A | 250V | 3 |
| GGM4/10 | GGM-V4/10 | 4/10A | 250V | 1 |
| GGM1/2 | GGM-V1/2 | 1/2A | 250V | 3 |
| GGM6/10 | GGM-V6/10 | 6/10A | 250V | 1 |
| GGM7/10 | GGM-V7/10 | 7/10A | 250V | 3 |
| GGM3/4 | GGM-V3/4 | 3/4A | 250V | 3 |
| GGM8/10 | GGM-V8/10 | 8/10A | 250V | 1 |
| GGM1 | GGM-V1 | 1A | 250V | 3 |
| GGM1-2/10 | N/A | 1-2/10A | 250V | 2 |
| GGM1-1/4 | GGM-V1-1/4 | 1-1/4A | 250V | 3 |
| GGM1-1/2 | GGM-V1-1/2 | 1-1/2A | 250V | 3 |
| GGM2 | GGM-V2 | 2A | 250V | 3 |
| GGM2-1/2 | GGM-V2-1/2 | 2-1/2A | 250V | 3 |
| GGM3 | GGM-V3 | 3A | 250V | 3 |
| GGM4 | GGM-V4 | 4A | 125V | 4 |
| GGM5 | GGM-V5 | 5A | 125V | 4 |
| GGM6 | GGM-V6 | 6A | 125V | 4 |
| GGM7 | GGM-V7 | 7A | 125V | 4 |
| GGM8 | GGM-V8 | 8A | 125V | 4 |
| GGM15 | GGM-V15 | 15A | 250V | 5 |

1. 250VAC @ 35A I.R./125VAC @ 10kA I.R.
2. 250VAC @ 100A I.R./125VAC @ 10kA I.R.
3. 250VAC @ 200A I.R./125VAC @ 10kA I.R.
4. 125VAC @ 10kA I.R.
5. 250VAC @ 100A I.R.

MF